

Сервоприводы VH200

Технические характеристики

По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(727)345-47-04

Беларусь +375-257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: agy@nt-rt.ru || сайт: <https://laeg.nt-rt.ru>

VH200 Servo Driver



VH series Servo driver

VH200 - 2R8 B P - A 1 - other

Mark	Type
VH200	Servo driver

Mark	Type
1R6	1.6A
2R8	2.8A
3R5	3.5A
5R4	5.4A
5R5	5.5A
.....

Mark	Rated voltage
B	220V
D	380V

Mark	Type
1	17-bit single-coil magnetic encoder
2	17-bit photoelectric encoder
3	23-bit photoelectric encoder

Mark	Type
A	Communication encoder
B	Incremental encoder

Mark	Type
P	Pulse mode
C	CNAopen bus type
N	EtherCAT bus type
F	PROFINET bus type



Electrical specifications for single-phase 220V rated drives

Item	SIZE A		
	1R6B	2R8B	5B5B
Drive Model	1R6B	2R8B	5B5B
Drive power (kW)	0.2	0.4	0.75
Maximum applicable motor capacity (kW)	0.2	0.4	0.75
Continuous output current (A)	1.6	2.8	5.5
Maximum output current (A)	5.8	10.1	16.9
Main circuit power supply	Single-phase AC200V ~ 240V, -15 ~ +10%, 50/60Hz		
Control circuit power supply	Single-phase AC200V ~ 240V, -15 ~ +10%, 50/60Hz		
Brake Drain Function	External braking resistor, internal braking resistor		

Three-phase 220V rated drive electrical specifications

Item	SIZE A	SIZE C	
	5R5B	7R6B	012B
Drive Model	5R5B	7R6B	012B
Drive power (kW)	0.8	1	1.5
Maximum applicable motor capacity (kW)	0.8	1	1.5
Continuous output current (A)	5.5	7.6	11.6
Maximum output current (A)	16.9	17	28

Main circuit power supply	Three-phase AC200V ~ 240V, -15 ~ +10%,50/60Hz
Control circuit power supply	Single-phase AC200V ~ 240V, -15 ~ +10%, 50/60Hz
Brake Drain Function	Built-in braking resistor

Three-phase 380V rated drive electrical specifications

Three-phase 380V rated drive electrical specifications							
Item	SIZE C				SIZE E		
Drive Model	2850	5R4D	8R4D	012D	017D	021D	026D
Drive power (kW)	1	1.5	2.2	3	4	5.5	7.5
Maximum applicable motor capacity (kW)	1	1.5	2.2	3	4	5.5	7.5
Continuous output current (A)	3.5	5.4	8.4	11.9	16.5	20.8	25.7
Maximum output current (A)	8.5	14	20	24	42	55	65
Main circuit power supply	Three-phase AC380V ~ 440V,-15 +10%, 50/60Hz						
Control circuit power supply	Single-phase AC380V ~ 440V,-15 ~ +10%,50/60Hz						
Brake Drain Function	Built-in braking resistor						

По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(727)345-47-04

Беларусь +375-257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: agy@nt-rt.ru || сайт: <https://laeg.nt-rt.ru>