

# Преобразователи энергии Orion 030 / Orion 040 / Orion 050

## Технические характеристики

По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04  
Ангарск (3955)60-70-56  
Архангельск (8182)63-90-72  
Астрахань (8512)99-46-04  
Барнаул (3852)73-04-60  
Белгород (4722)40-23-64  
Благовещенск (4162)22-76-07  
Брянск (4832)59-03-52  
Владивосток (423)249-28-31  
Владикавказ (8672)28-90-48  
Владимир (4922)49-43-18  
Волгоград (844)278-03-48  
Вологда (8172)26-41-59  
Воронеж (473)204-51-73  
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06  
Ижевск (3412)26-03-58  
Иркутск (395)279-98-46  
Казань (843)206-01-48  
Калининград (4012)72-03-81  
Калуга (4842)92-23-67  
Кемерово (3842)65-04-62  
Киров (8332)68-02-04  
Коломна (4966)23-41-49  
Кострома (4942)77-07-48  
Краснодар (861)203-40-90  
Красноярск (391)204-63-61  
Курск (4712)77-13-04  
Курган (3522)50-90-47  
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13  
Москва (495)268-04-70  
Мурманск (8152)59-64-93  
Набережные Челны (8552)20-53-41  
Нижний Новгород (831)429-08-12  
Новокузнецк (3843)20-46-81  
Ноябрьск (3496)41-32-12  
Новосибирск (383)227-86-73  
Омск (3812)21-46-40  
Орел (4862)44-53-42  
Оренбург (3532)37-68-04  
Пенза (8412)22-31-16  
Петрозаводск (8142)55-98-37  
Псков (8112)59-10-37  
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15  
Рязань (4912)46-61-64  
Самара (846)206-03-16  
Санкт-Петербург (812)309-46-40  
Саратов (845)249-38-78  
Севастополь (8692)22-31-93  
Саранск (8342)22-96-24  
Симферополь (3652)67-13-56  
Смоленск (4812)29-41-54  
Сочи (862)225-72-31  
Ставрополь (8652)20-65-13  
Сургут (3462)77-98-35  
Сыктывкар (8212)25-95-17  
Тамбов (4752)50-40-97  
Тверь (4822)63-31-35

Тольятти (8482)63-91-07  
Томск (3822)98-41-53  
Тула (4872)33-79-87  
Тюмень (3452)66-21-18  
Ульяновск (8422)24-23-59  
Улан-Удэ (3012)59-97-51  
Уфа (347)229-48-12  
Хабаровск (4212)92-98-04  
Чебоксары (8352)28-53-07  
Челябинск (351)202-03-61  
Череповец (8202)49-02-64  
Чита (3022)38-34-83  
Якутск (4112)23-90-97  
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(727)345-47-04

Беларусь +375-257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: [agy@nt-rt.ru](mailto:agy@nt-rt.ru) || сайт: <https://laeg.nt-rt.ru>

## Orion050/Orion040/Orion030 Energy Storage Converters



Model	Orion030	Orion040	Orion050
<b>DC characteristics</b>			
Maximum DC Voltage	800vdc		
Minimum DC Voltage	600vdc		
DC Operating Voltage Range	650~800vdc	650~800vdc	650~800vdc
Maximum DC Current	55A	70A	86A
Number of DC Inputs channels	1		
<b>AC characteristics (grid-connected)</b>			
Rated Output Power	30kW	40kW	50kW
Maximum Output Power	33kVA	44kVA	55kVA
Maximum Output Current	48A	64A	80A
Rated Grid Voltage	400Vac		
AC Voltage Range	-15%~10%(Adjustable Range)		
Rated Grid Frequency / Grid Frequency Range	50Hz/45-55Hz(Configurable up to 60Hz)		
AC Current Harmonics	<3%Un(Based on Rated Output Power)		
Power Factor at Rated Power	>0.99(Based on Rated Output Power)		
Reactive Power Adjustable Range	-100%~100%		
Number of Feeding Phases/Number of Output Phases	3-Phase/3-Wire		
Overload Capability	110% Overload		
<b>AC characteristics (off-grid)</b>			
Rated Output Power	30kW	40kW	50kW
Maximum Output Power	33kVA	44KVA	60kVA
Maximum Output Current	48A	64A	86A
Rated AC Voltage	400Vac		

AC Voltage Range	-15%~10%(Adjustable Range)
AC Voltage Harmonics	<3%(Linear Load)
DC Voltage Component	<1%Un(Linear Balanced Load)
Unbalanced Load Capability	110% Overload
Rated Grid Frequency / Grid Frequency Range	50Hz/45-55Hz(Configurable up to 60Hz)
<b>Efficiency</b>	
Maximum Efficiency	98.6%
<b>Protection</b>	
DC Input Protection	Fuse
AC Surge Protection	AC Typell
Grid Monitoring/Insulation Monitoring	Y/Y
Reverse Polarity Protection/Overheat Protection	Y/Y
<b>Basic Parameters</b>	
Parallel Operation Function	Y
Isolation Type	Transformerless Isolation
IP Grade	IP21
Operating Temperature Range	-35°Cto +60°C(Derated Operation above 45°C)
Relative Humidity Range	0 to 100%(Condensation-Free)
Cooling Method	Forced Intelligent Air Cooling
Maximum Operating Altitude	4000m(Derated Operation above 2000m)
Installation Method	Wall-Mounted, Rack-Mounted
Dimensions (W x H x D)	420×132x600mm(Standard Enclosure with 3U Height)
Weight	30kg
Display	LED, Upper Computer
Communication Interface	WIFI/RS485/CAN/ Ethernet
Communication Protocol	Modbus-RTU/Modbus-TCP/IEC61850/IEC104/CAN2.0B
Grid Support	Active and Reactive Power Control, Power Slope Control
Compliance with Standards	GB/T34133-2023,GB/T 34120-2023,IEC62477-1

## По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04  
Ангарск (3955)60-70-56  
Архангельск (8182)63-90-72  
Астрахань (8512)99-46-04  
Барнаул (3852)73-04-60  
Белгород (4722)40-23-64  
Благовещенск (4162)22-76-07  
Брянск (4832)59-03-52  
Владивосток (423)249-28-31  
Владикавказ (8672)28-90-48  
Владимир (4922)49-43-18  
Волгоград (844)278-03-48  
Вологда (8172)26-41-59  
Воронеж (473)204-51-73  
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06  
Ижевск (3412)26-03-58  
Иркутск (395)279-98-46  
Казань (843)206-01-48  
Калининград (4012)72-03-81  
Калуга (4842)92-23-67  
Кемерово (3842)65-04-62  
Киров (8332)68-02-04  
Коломна (4966)23-41-49  
Кострома (4942)77-07-48  
Краснодар (861)203-40-90  
Красноярск (391)204-63-61  
Курск (4712)77-13-04  
Курган (3522)50-90-47  
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13  
Москва (495)268-04-70  
Мурманск (8152)59-64-93  
Набережные Челны (8552)20-53-41  
Нижний Новгород (831)429-08-12  
Новокузнецк (3843)20-46-81  
Ноябрьск (3496)41-32-12  
Новосибирск (383)227-86-73  
Омск (3812)21-46-40  
Орел (4862)44-53-42  
Оренбург (3532)37-68-04  
Пенза (8412)22-31-16  
Петрозаводск (8142)55-98-37  
Псков (8112)59-10-37  
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15  
Рязань (4912)46-61-64  
Самара (846)206-03-16  
Санкт-Петербург (812)309-46-40  
Саратов (845)249-38-78  
Севастополь (8692)22-31-93  
Саранск (8342)22-96-24  
Симферополь (3652)67-13-56  
Смоленск (4812)29-41-54  
Сочи (862)225-72-31  
Ставрополь (8652)20-65-13  
Сургут (3462)77-98-35  
Сыктывкар (8212)25-95-17  
Тамбов (4752)50-40-97  
Тверь (4822)63-31-35

Тольятти (8482)63-91-07  
Томск (3822)98-41-53  
Тула (4872)33-79-87  
Тюмень (3452)66-21-18  
Ульяновск (8422)24-23-59  
Улан-Удэ (3012)59-97-51  
Уфа (347)229-48-12  
Хабаровск (4212)92-98-04  
Чебоксары (8352)28-53-07  
Челябинск (351)202-03-61  
Череповец (8202)49-02-64  
Чита (3022)38-34-83  
Якутск (4112)23-90-97  
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(727)345-47-04

Беларусь +375-257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: [agy@nt-rt.ru](mailto:agy@nt-rt.ru) || сайт: <https://laeg.nt-rt.ru>